



ANCO Leuchten KG
EyrS - Gewerbegebiet 1
39023 - Laas (BZ)
Italien

IT00222550212
www.ancoleuchten.it
info@ancoleuchten.it
+39 0473739788

Automatisch generiertes
Dokument.
Technische Änderungen
vorbehalten.

Panoramica

Alimentatore Multicurrent 60W DIMM



Codice prodotto: D10LCM-60DA2



■ DIP SWITCH TABLE
LCM 60DA2 is a multi-stage constant current driver.
Selection of output current through DIP switch is as follows.

Output Current	1	2	3	4	5
500mA	ON	ON	ON	ON	ON
600mA	ON	ON	ON	ON	OFF
700mA	ON	ON	ON	OFF	OFF
900mA	ON	ON	OFF	OFF	OFF
1050mA	ON	OFF	OFF	OFF	OFF
1400mA	OFF	OFF	OFF	OFF	OFF

Note: For more current setting please contact MW's sales.

Descrizione

Driver a corrente costante con uscita a corrente multipla regolabile tramite DIP-Switch. Max. 60W, 180-295Vac, uscita 500/600/700/900/1050/1400mA. Dimmerabile tramite DALI/Push/1-10V/PWM/Potenzziometro. Grado di protezione IP20, custodia in plastica. Dimensioni: 123,5x81,5xH23mm.

Dokument erstellt am 31.05.2026.

Dieses Dokument wurde automatisch generiert. Technische Änderungen vorbehalten. Alle Angaben ohne Gewähr.

* Tutti i prezzi escl. IVA più spese di spedizione ed eventuali spese di spedizione, se non diversamente indicato.